LD SERIES LD1.0/2.0/3.0



LDx.0 amplifiers from Opus Technologies are next generation induction loop Class-D amplifiers. The one channel amplifiers offer all the functionalities (AGC, MLC, compressor, etc) to ensure room installations up to 250m² (LD1.0), 450m² (LD2.0) or 1000m² (LD3.0).

Thanks to high frequency switching mode proprietary solutions, the amplifiers are one of the most compact on the market and do not need any active cooling. They include a LEDs indicator fault synthesis on the driver's front panel to control the integrity of both loop and amplifier. Informations can be deported thanks to a dry contact relay.

The high-grade power supply and output voltage capability (48Vpk) ensure outstanding sound quality with high dynamic and extremely low distorsion.

The amplifiers can also be used in a low diaphonic phased loop system or an ultra high coverage system with a built-in 90 ° or 0 ° phase shift module (2 amplifiers).

Amplifiers have been developed with strict and rigorous specifications that allow us to offer a 5 year warranty and meet the IEC 60118-4. LD1.0, LD2.0,LD3.0 amplifiers follow strict specifications required for UL compliance.

- ✓ One channel amplifier
- ✓ High frequency switching mode
- ✓ Efficiency up to 92%
- ✓ Natural cooling
- ✓ AGC: Automatic Gain Control optimized for speech
- ✓ 3 inputs wirh selectable gain
- ✓ 70/100V priority alarm input
- ✓ Phantom supply for microphone
- ✓ Slave amplifier input, output and 90% dephased output
- ✓ Adjustable metal losses correction
- ✓ 1U wall mounting available
- ✓ Compact and light
- √ 5-Year warranty
- ✓ LEDs indicator
- ✓ Relay fault systhesis
- ✓ IEC 62368/UL compliant
- Over current, over temperature and short circuit protections





Coverage

Cover meets the IEC 60118-4 standard


| | No metal loss | | | Moderate metal loss | | | High metal loss | | |
|-------|------------------------------|---------------------------------|---------------------|-------------------------------|----------------------|---------------------|--|-----------------|-------------------|
| Loop | Perimeter loop | Single array in 8 | Low overspill* | Perimeter loop | Single array in 8 | Low overspill* | Perimeter loop | Single array | Low overspill* |
| LD1.0 | 250m² (10x25m) | 450m² (15x30m) | 450m² (15x30m) | 130m² (10x13m) | 180m² (10x18m) | 450m² (15x30m) | Use Multi Loop Systems LDx.2 and/or Contact us | | |
| LD2.0 | 450m ² (15x30m) | 650m² (20x32,5m) | 650m² (20x32,5m) | 160m ² (10x16m) | 280m² (8x35m) | 650m² (20x32,5m) | | | |
| LD3.0 | 1 000m ² (16x62m) | 1 400m ² (35x40m) | 1 400m² (35x40m) | 250m ² (10x25m) | 360m² (10x36m) | 1 400m² (35x40m) | | | |

^{*}with 2 amplifiers





LD SERIES LD1.0/2.0/3.0



| | LD1.0 | LD2.0 | LD3.0 | |
|---|--|--|---|--|
| Coverage surface | 250 m² (10*25 m²) | 450 m² (15*30 m²) | 1000 m² (20*45 m²) | |
| Power input | | | | |
| Voltage | 100-240Vac, 50-60Hz | 100-240Vac, 50-60Hz | 100-240Vac, 50-60Hz | |
| Consumption at idle with 1Ω loop connected | 9W at 230Vac and 25°C ambient temperature | 9W at 230Vac and 25°C ambient temperature | 9W at 230Vac and 25°C ambient temperature | |
| Nominal power consum Ption at 1Ω | 25W | 50W | 90W | |
| Maximum power consumption | <250 VA | <300 VA | <350 VA | |
| Connector | IEC C13 | IEC C13 | IEC C13 | |
| Audio input | | | | |
| Input channels with separated adjustable gain | Input 1: 70/100V signal (priority dignal) Input 2: Microphone or line Input 3: Microphone or line | Input 1: 70/100V signal (priority dignal) Input 2: Microphone or line Input 3: Microphone or line | Input 1: 70/100V signal (priority dignal) Input 2: Microphone or line Input 3: Microphone or line | |
| Phantom supply | Available on microphone inputs: 12V | Avaiblable on microphone inputs: 12V | Available on microphone inputs: 12V | |
| Sensitivity | Microphone: -50 dBLine: -10 dB100V: +40 dB | Microphone: -50 dBLine: -10 dB100V: +40 dB | Microphone: -50 dBLine: -10 dB100V: +40 dB | |
| Connector | MTSB terminal block and/or Combo Neutrik for input 3 | MTSB terminal block and/or Combo Neutrik for input 3 | MTSB terminal block and/or Combo Neutrik for input 3 | |
| Audio ouput | | | | |
| Loop impedance | 0.5 Ω to 3 Ω | 0.5 Ω to 3 Ω | 0.5 Ω to 3 Ω | |
| Max ouput current | 5 Arms, 7 Apeak | 7.5 Arms, 10Apeak | 10 Arms, 14Apeak | |
| Max output voltage | 34 Vrms, 48 Vpeak | 34 Vrms, 48 Vpeak | 34 Vrms, 48 Vpeak | |
| THD | <0.5% at nominal ouput current, 1Ω loop, -3 dB | <0.5% at nominal ouput current, 1Ω loop, -3 dB | <0.5% at nominal ouput current, 1Ω loop, -3 dB | |
| Bandwidth | 80 Hz to 9.5 kHz, -3 dB | 80 Hz to 9.5 kHz, -3 dB | 80 Hz to 9.5 kHz, -3 dB | |





| | LD1.0 | LD2.0 | LD3.0 | | |
|--|--|--|--|--|--|
| Audio output | | | | | |
| Dynamic | >36 dB | >36 dB | >36 dB | | |
| Metal loss correction | 0 to 3dB per octave filter | 0 to 3dB per octave filter | 0 to 3dB per octave filter | | |
| Connector | MTSBA terminal block | MTSBA terminal block | MTSBA terminal block | | |
| Slave Amplifier | | | | | |
| Input / outputs | One input, one direct output and one 90° dephased output | One input, one direct output and one 90° dephased output | One input, one direct output and one 90° dephased output | | |
| Connectors | Jack 6.35 mm | Jack 6.35 mm | Jack 6.35 mm | | |
| LEDs indicator | | | | | |
| « Power » | Switched on when module powered | Switched on when module powered | Switched on when module powered | | |
| « Protect » | Switched on when signal clippi | ng, too high temperature reache | d or in case of loop failure | | |
| « Loop » | Switched on when the loop is in working conditions | Switched on when the loop is in working conditions | Switched on when theloop is in working conditions | | |
| « Clip » | Switched on when signal clipping | Switched on when signal clipping | Switched on when signal clipping | | |
| Vu meters « Input » | Input signal level after adjustement | Input signal level after adjustement | Input signal level after adjustement | | |
| Vu-meters « output » | Percentage of maximum current drawn | Percentage of maximum current drawn | Percentage of maximum current drawn | | |
| NO/NC fault relay synthesis (contact closed once one fault is detected) | | | | | |
| Detected faults | Too high temperature raised and loop failure | Too high temperature raised and loop failure | Too high temperature raised and loop failure | | |
| Maximum electrical rating | 0.5A/125Vac or 1A/24Vdc | 0.5A/125Vac or 1A/24Vdc | 0.5A/125Vac or 1A/24Vdc | | |
| Connector | MTSB terminal block | MTSB terminal block | MTSB terminal block | | |
| General | | | | | |
| Protections | Over current, over temperature, short circuit | Over current, over temperature, short circuit | Over current, over temperature, short circuit | | |
| Operating temperatur | 0 to + 45°C | 0 to + 45°C | 0 to + 45°C | | |
| Storage temperature | -30 to +70°C | -30 to +70°C | -30 to +70°C | | |
| Size | 42x200x215 mm / 1.6x7.9x8.5 inch | 42x200x215 mm / 1.6x7.9x8.5 inch | 42x200x215 mm / 1.6x7.9x8.5 inch | | |
| Weight | 1,56kg / 3,43lbs | 1,56kg / 3,43lbs | 1,56kg / 3,43lbs | | |



